

Item: 88407-SU



Ballast Description					Reduced Lamp Load*		Rated Lamp Load	
No.	Brand	Model	Start Method	No. of Lamps	120V	277V	120V	277V
1	ACT	ACT 2P32ISUNVE	IS	2	✓	✓	✓	✓
2	Antron Electronics	A32T8MICLO	IS	2	✓	✗	✓	✓
3	Arcara	ACT 3P32ISUNVLE	IS	3	✓	✓	✓	✓
4	Damar	EL232-120/277HF(1688B)	IS	2	✓	✗	✓	✓
5	Damar	EL232DIM/120/277HF	DPS	2	✗	✗	✗	✗
6	Damar	EL232HL-120/277HF(1688D)	IS	2	✓	✓	✓	✓
7	Damar	EL332-120/277HF(3654C)	IS	3	✓	✓	✓	✓
8	Damar	EL332HL-120/277HF(3654H)	IS	3	✓	✓	✓	✓
9	Damar	EL432-120/277HF(3093B)	IS	4	✓	✓	✓	✓
10	Damar	EL432HL-120/277HF(3093C)	IS	4	✓	✓	✓	✓
11	Eiko	PM-2×32T8-UNV-IS-H	IS	2	✓	✓	✓	✓
12	Eiko	PM-2×32T8-UNV-PS	PS	2	✗	✗	✗	✗
13	Eiko	PM-2X32T8-UNV-IS	IS	2	✓	✓	✓	✓
14	Eiko	PM-2X32T8-UNV-IS-L	IS	2	✓	✓	✓	✓
15	Eiko	PM-3X32T8-UNV-IS	IS	3	✓	✓	✓	✓
16	Eiko	PM-3X32T8-UNV-IS-H	IS	3	✓	✓	✓	✓
17	Eiko	PM-3X32T8-UNV-IS-L	IS	3	✓	✓	✓	✓
18	Eiko	PM-3X32T8-UNV-PS	PS	3	✗	✗	✗	✗
19	Eiko	PM-3X32T8-UNV-PS-H	PS	3	✗	✗	✗	✗
20	Eiko	PM-4X32T8-UNV-IS	IS	4	✓	✓	✓	✓
21	Eiko	PM-4X32T8-UNV-IS-L	IS	4	✓	✓	✓	✓
22	Espen	VE232MVHIPE	IS	2	✓	✓	✓	✓
23	Espen	VE232MVHIPHE	IS	2	✓	✓	✓	✓
24	Espen	VE232MVHIPL	IS	2	✓	✓	✓	✓
25	Espen	VE232MVHRPHT3-AB	DPS	2	✗	✗	✗	✗

Ballast Description					Reduced Lamp Load*		Rated Lamp Load	
No.	Brand	Model	Start Method	No. of Lamps	120V	277V	120V	277V
26	Espen	VE2P32MVHIPE	IS	2	✓	✓	✓	✓
27	General Electric	332MAX-H-42T	IS	3	✗	✗	✗	✗
28	General Electric	332MAX-H-84TS	IS	3	✗	✗	✗	✗
29	General Electric	GE132MAX-G-N	IS	1	N/A	N/A	✗	✗
30	General Electric	GE132MAX-H/ULTRA	IS	1	N/A	N/A	✓	✓
31	General Electric	GE132MAX-L/ULTRA	IS	1	N/A	N/A	✗	✗
32	General Electric	GE132MAXP-N/ULTRA	IS	1	N/A	N/A	✓	✓
33	General Electric	GE132MVPSN-V03	DPS	1	N/A	N/A	✗	✗
34	General Electric	GE232MAX-G-L	IS	2	✓	✓	✓	✓
35	General Electric	GE232MAX-G-N	IS	2	✓	✓	✓	✓
36	General Electric	GE-232-MAX-H/Ultra	IS	2	✗	✗	✗	✗
37	General Electric	GE-232-MAX-H-42T	IS	2	✗	✗	✗	✗
38	General Electric	GE232MAX-L/ULTRA	IS	2	✗	✗	✗	✗
39	General Electric	GE232MAX-N/ULTRA	IS	2	✓	✓	✓	✓
40	General Electric	GE232MAXP90-V60	IS	2	✗	✗	✗	✗
41	General Electric	GE232MAXP-N/ULTRA	IS	2	✗	✗	✗	✗
42	General Electric	GE-232-MV-N	IS	2	✓	✓	✓	✓
43	General Electric	GE232MV-N-DIY	IS	2	✗	✗	✗	✗
44	General Electric	GE232MVPS-L-S30	DPS	2	✗	✗	✗	✗
45	General Electric	GE232-MVPS-N	PS	2	✓	✗	✓	✗
46	General Electric	GE-232-MV-PS-N	PS	2	✓	✓	✓	✓
47	General Electric	GE332MAX-G-N	IS	3	✓	✓	✓	✓
48	General Electric	GE332MAX-L/ULTRA	IS	3	✓	✓	✓	✓
49	General Electric	GE332MAX-N/ULTRA	IS	3	✗	✗	✓	✓
50	General Electric	GE332MAXP90-V60	IS	3	✓	✓	✓	✓
51	General Electric	GE332MAXP-H/ULTRA	IS	3	✓	✓	✓	✓
52	General Electric	GE332MAXP-L/ULTRA	IS	3	✓	✓	✓	✓
53	General Electric	GE332MAXP-N/ULTRA	IS	3	✓	✓	✓	✓
54	General Electric	GE332MV-N	IS	3	✓	✓	✓	✓
55	General Electric	GE-332-MVPS-H	PS	3	✗	✗	✗	✗

Ballast Description					Reduced Lamp Load*		Rated Lamp Load	
No.	Brand	Model	Start Method	No. of Lamps	120V	277V	120V	277V
56	General Electric	GE-332-MVPS-N	PS	3	✓	✓	✓	✓
57	General Electric	GE332MVPSN-V03	DPS	3	✗	✗	✗	✗
58	General Electric	GE432-120-RES	IS	4	✓	N/A	✓	N/A
59	General Electric	GE432MAX90-S60	IS	4	✓	✓	✓	✓
60	General Electric	GE432MAX-G-H	IS	4	✗	✗	✗	✗
61	General Electric	GE432MAX-G-N	IS	4	✓	✓	✓	✓
62	General Electric	GE432MAX-H/ULTRA	IS	4	✓	✓	✓	✓
63	General Electric	GE432MAX-H-42T	IS	4	✗	✗	✗	✗
64	General Electric	GE432MAX-L/ULTRA	IS	4	✗	✗	✗	✗
65	General Electric	GE432MAX-N/ULTRA	IS	4	✓	✓	✓	✓
66	General Electric	GE432MAXP90-S60	IS	4	✓	✓	✓	✓
67	General Electric	GE432MV-N	IS	4	✗	✗	✗	✗
68	General Electric	GE432MV-N-42T	IS	4	✗	✗	✗	✗
69	General Electric	GE432-MVPS-N	PS	4	✓	✓	✓	✓
70	General Electric	GE432MVPS-N-V03	PS	4	✗	✗	✗	✗
71	Halco	EP232IS/H/MV/HE	IS	2	✓	✓	✓	✓
72	Halco	EP232IS/L/MV/HE	IS	2	✓	✓	✓	✓
73	Halco	EP232IS/MV/HE	IS	2	✓	✓	✓	✓
74	Halco	EP332IS/L/MV/HE	IS	3	✓	✓	✓	✓
75	Halco	EP332IS/MV/HE	IS	3	✓	✓	✓	✓
76	Halco	EP432IS/120/MC	IS	4	✓	✓	✓	✓
77	Halco	EP432IS/L/MV/HE	IS	4	✓	✓	✓	✓
78	Halco	EP432IS/MV/HE	IS	4	✓	✓	✓	✓
79	Hatch	HL232BIS/UV/HE/W	IS	2	✓	✗	✓	✓
80	Hatch	HL432BIS/UV/HE/W	IS	4	✓	✓	✓	✓
81	Howard Industries	E2/32IS-120MC	IS	2	✓	N/A	✓	N/A
82	Howard Industries	EP2/32IS/MV/MC/HE	IS	2	✓	✓	✓	✓
83	Howard Industries	EP2/32PRS/MV/MC/HE	PRS	2	✗	✗	✗	✗
84	Howard Industries	EP3 32IS MV MC HE	IS	3	✓	✓	✓	✓
85	Howard Industries	EP3/32IS/MV/SC/HE	IS	3	✓	✓	✓	✓

Ballast Description					Reduced Lamp Load*		Rated Lamp Load	
No.	Brand	Model	Start Method	No. of Lamps	120V	277V	120V	277V
86	Howard Industries	EP4/32IS/MV/MC/HE	IS	4	✓	✓	✓	✓
87	Howard Industries	EPH2/321S/MV/MC/HE	IS	2	✓	✓	✓	✓
88	Howard Industries	EPH3/32IS/MV/MC/HE	IS	3	✓	✓	✓	✓
89	Howard Industries	EPH4/32IS/MV/SC/HE	IS	4	✗	✗	✗	✗
90	Howard Industries	EPL2/32IS/MV/MC/HE	IS	2	✓	✓	✓	✗
91	Howard Industries	EPL3/32IS/MV/SC/HE	IS	3	✓	✓	✓	✓
92	Howard Industries	EPL4/32IS/MV/MC/HE	IS	4	✓	✓	✓	✓
93	Keystone	KTEB-132-1-TP-FC	RS	1	N/A	N/A	✓	N/A
94	Keystone	KTEB-232LBF-1-TP-PIC-EV	IS	2	✓	N/A	✓	N/A
95	Keystone	KTEB-232-UV-IS-H-P	IS	2	✓	✓	✓	✓
96	Keystone	KTEB-232-UV-IS-L-P	IS	2	✓	✓	✓	✓
97	Keystone	KTEB-232-UV-IS-N-P	IS	2	✓	✓	✓	✓
98	Keystone	KTEB-332-UV-IS-H-P	IS	3	✗	✗	✗	✗
99	Keystone	KTEB-332-UV-IS-N-P	IS	3	✓	✓	✓	✓
100	Keystone	KTEB-432RIS-1-TP-SL	IS	4	✓	N/A	✓	N/A
101	Keystone	KTEB-432-UV-IS-H-P	IS	4	✓	✓	✓	✓
102	Keystone	KTEB-432-UV-IS-N-P	IS	4	✓	✓	✓	✓
103	Lighting Products Limited	EB-332EBF-UV-TP-HE	IS	3	✓	✓	✓	✓
104	Maxlite	MLEU322HEL/SC	IS	2	✓	✓	✓	✓
105	Maxlite	MLEU323H/SC	IS	3	✓	✓	✓	✓
106	Maxlite	MLEU324HE/SC	IS	4	✓	✓	✓	✓
107	Maxlite	SKEU322HEL/SC	IS	2	✓	✓	✓	✓
108	Maxlite	SKEU323L/SC	IS	3	✓	✓	✓	✓
109	Maxlite	SKEU324HE/SC	IS	4	✓	✓	✓	✓
110	Motorola	M2-IN-T8-GP-D-277	IS	2	N/A	✓	N/A	✓
111	Motorola	M3-IN-T8-GP-A-277	IS	3	N/A	✓	N/A	✓
112	Osram Sylvania	QHE 1X32T8/UNV DIM-TC	DPS	1	N/A	N/A	✗	✗
113	Osram Sylvania	QHE 1X32T8/UNV ISH-SC	IS	1	N/A	N/A	✓	✓
114	Osram Sylvania	QHE 1X32T8/UNV ISL-SC	IS	1	N/A	N/A	✓	✓
115	Osram Sylvania	QHE 1X32T8/UNV ISN-SC	IS	1	N/A	N/A	✓	✓

Ballast Description					Reduced Lamp Load*		Rated Lamp Load	
No.	Brand	Model	Start Method	No. of Lamps	120V	277V	120V	277V
116	Osram Sylvania	QHE 2X32T8/UNV DIM-TC	PRS	2	✗	✗	✗	✗
117	Osram Sylvania	QHE 2X32T8/UNV ISH HT-S	IS	2	✓	✓	✓	✓
118	Osram Sylvania	QHE 2X32T8/UNV ISH-SC	IS	2	✓	✓	✗	✓
119	Osram Sylvania	QHE 2X32T8/UNV ISL-SC	IS	2	✓	✓	✓	✓
120	Osram Sylvania	QHE 2X32T8/UNV ISN-SC	IS	2	✓	✓	✓	✓
121	Osram Sylvania	QHE 2X32T8/UNV PSH-HT	PRS	2	✗	✗	✗	✗
122	Osram Sylvania	QHE 2X32T8/UNV PSN-MC	PRS	2	✓	✓	✓	✓
123	Osram Sylvania	QHE 3x32T8/UNV ISH HT-S	IS	3	✓	✓	✓	✓
124	Osram Sylvania	QHE 3X32T8/UNV ISH-SC	IS	3	✗	✗	✗	✗
125	Osram Sylvania	QHE 3X32T8/UNV ISL-SC	IS	3	✓	✓	✓	✓
126	Osram Sylvania	QHE 3X32T8/UNV ISN-SC	IS	4	✓	✓	✓	✓
127	Osram Sylvania	QHE 3X32T8/UNV PSN-SC	PRS	3	✗	✗	✗	✗
128	Osram Sylvania	QHE 4X32T8/UNV ISH	IS	4	✗	✗	✗	✗
129	Osram Sylvania	QHE 4x32T8/UNV ISH HT-1	IS	4	✓	✓	✓	✓
130	Osram Sylvania	QHE 4x32T8/UNV ISH-SC	IS	4	✗	✗	✗	✗
131	Osram Sylvania	QHE 4X32T8/UNV ISL-SC	IS	4	✓	✓	✓	✓
132	Osram Sylvania	QHE 4X32T8/UNV ISN-SC	IS	4	✓	✓	✓	✓
133	Osram Sylvania	QHE 4X32T8/UNV PSN-SC	PRS	4	✓	✓	✓	✓
134	Osram Sylvania	QHE 4X32T8/UNV PSX-SC	PRS	4	✗	✗	✗	✗
135	Osram Sylvania	QHES 2x32T8/UNV PSL-SC	PRS	2	✗	✗	✓	✓
136	Osram Sylvania	QT2X32/120 IS-SC	IS	2	✓	N/A	✓	N/A
137	Osram Sylvania	QT3x32T8/277 ISN-A	IS	3	N/A	✓	N/A	✓
138	Osram Sylvania	QTP 2X32T8/UNV ISL-SC	IS	2	✓	✓	✓	✓
139	Osram Sylvania	QTP 2X32T8/UNV ISN-SC	IS	2	✓	✓	✓	✓
140	Osram Sylvania	QTP 3X32T8/UNV ISN-SC	IS	3	✓	✓	✓	✓
141	Osram Sylvania	QTP 3X32T8/UNV PSX-SC	PRS	3	✗	✗	✗	✗
142	Osram Sylvania	QTP2x32T8/UNV DIM-TC	DPS	2	✗	✗	✗	✗
143	Osram Sylvania	QTP2x32T8/277 ISN-D	IS	2	N/A	✓	N/A	✓
144	Osram Sylvania	QTP3X32T8/UNV PSN-SC	PRS	3	✗	✗	✗	✗
145	Pacific Fluorescent	EB-232IS-120-RES	IS	2	✓	N/A	✓	N/A

Ballast Description					Reduced Lamp Load*		Rated Lamp Load	
No.	Brand	Model	Start Method	No. of Lamps	120V	277V	120V	277V
146	Philips-Advance	ICN-132-MC	IS	1	N/A	N/A	✓	✓
147	Philips-Advance	ICN-1P32-N	IS	1	N/A	N/A	✗	✗
148	Philips-Advance	ICN-2P16-TLED-N	IS	2	✗	✗	✗	✗
149	Philips-Advance	ICN-2P32-N	IS	2	✓	✓	✓	✓
150	Philips-Advance	ICN-3P16-TLED-N	IS	3	✗	✗	✗	✗
151	Philips-Advance	ICN-3P32-N	IS	3	✗	✗	✗	✗
152	Philips-Advance	ICN-3P32-SC	IS	3	✗	✗	✗	✗
153	Philips-Advance	ICN-4P16-TLED-N	IS	4	✗	✗	✗	✗
154	Philips-Advance	ICN-4P32-N	IS	4	✗	✗	✗	✗
155	Philips-Advance	IOP-1P32-LW-N	IS	1	N/A	N/A	✓	✓
156	Philips-Advance	IOP-1P32-N	IS	1	✗	✗	✗	✗
157	Philips-Advance	IOP-1P32-SC	IS	1	N/A	N/A	✓	✓
158	Philips-Advance	IOP-2P32HL-SC	IS	2	✗	✗	✗	✗
159	Philips-Advance	IOP-2P32-LW-N	IS	2	✓	✓	✓	✓
160	Philips-Advance	IOP-2P32-LW-SC	IS	2	✓	✓	✓	✓
161	Philips-Advance	IOP-2P32-N	IS	2	✓	✓	✓	✓
162	Philips-Advance	IOP-2PSP32-LW-N	PS	2	✓	✓	✓	✓
163	Philips-Advance	IOP-2PSP32-N	PS	2	✗	✗	✗	✗
164	Philips-Advance	IOP-2S32-SC	PS	2	✗	✗	✗	✗
165	Philips-Advance	IOP-3P32HL-90C-SC	IS	3	✗	✗	✗	✗
166	Philips-Advance	IOP-3P32-LW-SC	IS	3	✓	✓	✗	✓
167	Philips-Advance	IOP-3P32-N	IS	3	✗	✗	✗	✗
168	Philips-Advance	IOP-3PSP32-LW-SC	PS	3	✓	✓	✓	✓
169	Philips-Advance	IOP-3PSP32-SC	PS	3	✓	✓	✓	✓
170	Philips-Advance	IOP-4P32-HL-SC	IS	4	✗	✗	✗	✗
171	Philips-Advance	IOP-4P32-LW-N	IS	4	✓	✓	✓	✓
172	Philips-Advance	IOP-4P32-LW-SC	IS	4	✗	✗	✗	✗
173	Philips-Advance	IOP-4P32-N	IS	4	✗	✗	✗	✗
174	Philips-Advance	IOP-4P32-SC	IS	4	✗	✗	✗	✗
175	Philips-Advance	IOP-4PSP32-LW-SC	PS	4	✗	✗	✗	✗

Ballast Description					Reduced Lamp Load*		Rated Lamp Load	
No.	Brand	Model	Start Method	No. of Lamps	120V	277V	120V	277V
176	Philips-Advance	IOP-4PSP32-SC	PS	4	✓	✓	✓	✓
177	Philips-Advance	IOPA-1P32-N	IS	1	✗	✗	✗	✗
178	Philips-Advance	IOPA-2P32-HL-N	IS	2	✗	✗	✗	✗
179	Philips-Advance	IOPA-2P32-LW-N	IS	2	✓	✓	✓	✓
180	Philips-Advance	IOPA-3P32-LW-N	IS	3	✗	✗	✗	✗
181	Philips-Advance	IOPA-3P32-LW-SC	IS	3	✓	✓	✓	✓
182	Philips-Advance	IOPA-3P32-N	IS	3	✗	✗	✗	✗
183	Philips-Advance	IOPA-4P32-HL	IS	4	✓	✓	✓	✓
184	Philips-Advance	IOPA-4P32-HL-SC	IS	4	✓	✓	✓	✓
185	Philips-Advance	IOPA-4P32-LW-N	IS	4	✓	✓	✓	✓
186	Philips-Advance	IOPA-4P32-N	IS	4	✗	✗	✗	✗
187	Philips-Advance	IOPA-4P32-SC	IS	4	✓	✓	✓	✓
188	Philips-Advance	IZT-2PSP32-SC	DPS	2	✗	✗	✗	✗
189	Philips-Advance	IZT-2S32-SC	DPS	2	✗	✗	✗	✗
190	Philips-Advance	IZT-3PSP32-SC	DPS	3	✗	✗	✗	✗
191	Philips-Advance	REB-2P32-SC	IS	2	✗	N/A	✗	N/A
192	Philips-Advance	REB-4P32-SC	IS	4	✓	N/A	✓	N/A
193	Philips-Advance	REL-2P32-RH-TP	IS	2	✓	N/A	✓	N/A
194	Philips-Advance	REZ-132-SC	DPS	1	N/A	N/A	✗	N/A
195	Philips-Advance	REZ-2S32-SC	DPS	2	✗	N/A	✗	N/A
196	Philips-Advance	REZ-3S32-SC	DPS	3	✗	N/A	✗	N/A
197	Philips-Advance	VEL-2P32-RH-TP	IS	2	N/A	✓	N/A	✓
198	Philips-Advance	VEL-2P32-SC	IS	2	N/A	✓	N/A	✓
199	Philips-Advance	VEL-3P32-SC	IS	3	N/A	N/A	N/A	N/A
200	Plusrite	BAF232IS/MV	IS	2	✓	✓	✓	✓
201	Plusrite	BAF232IS/MV/L	IS	2	✓	✓	✓	✓
202	Plusrite	BAF332IS/MV	IS	3	✓	✓	✓	✓
203	Plusrite	BAF332IS/MV/L	IS	3	✓	✓	✓	✓
204	Plusrite	BAF432IS/MV	IS	4	✓	✓	✓	✓
205	Plusrite	BAF432IS/MV/L	IS	4	✓	✓	✓	✓

Ballast Description					Reduced Lamp Load*		Rated Lamp Load	
No.	Brand	Model	Start Method	No. of Lamps	120V	277V	120V	277V
206	Prolume	E432IS/120/R/SL	IS	4	✓	N/A	✓	N/A
207	ProLume	EP232IS/L/MV/SL	IS	2	✓	✓	✓	✓
208	Sola	E-758-U-232-MC	IS	2	✓	✓	✓	✓
209	Sunpark	120-1/32IS HPF	IS	1	N/A	N/A	✓	N/A
210	Sunpark	120-3/32IS MPF	IS	3	✓	N/A	✓	N/A
211	Sunpark	LC 12011T	PS	1	N/A	N/A	✗	N/A
212	Sunpark	LC 12013T	PS	1	N/A	N/A	✗	N/A
213	Sunpark	SL15T	PS	2	✓	N/A	✓	N/A
214	Sunpark	U-1/32PSE	PS	1	N/A	N/A	✗	✗
215	Sunpark	U-2/32IS HBF	IS	2	✓	✓	✓	✓
216	Sunpark	U-2/32ISE-LBF	IS	2	✓	✓	✓	✓
217	Sunpark	U-2/32PSE	RS	2	✗	✗	✗	✗
218	Sunpark	U-2/32PSE-HBF	RS	2	✗	✗	✗	✗
219	Sunpark	U-232PS3	RS	2	✗	✗	✗	✗
220	Sunpark	U-232PS3-HBF	RS	2	✗	✗	✗	✗
221	Sunpark	U-3/32ISE	IS	3	✓	✓	✓	✓
222	Sunpark	U-3/32ISE-HBF	IS	3	✓	✓	✓	✓
223	Sunpark	U-4/32IS HBF	IS	4	✓	✓	✓	✓
224	Sunpark	U-4/32IS HPF	IS	4	✓	✓	✓	✓
225	Sunpark	U-4/32ISE-LBF	IS	4	✗	✗	✗	✗
226	Superior Life	70201	IS	2	✓	✓	✓	✓
227	Superior Life	70210	PS	2	✗	✗	✗	✗
228	Superior Life	70211	PS	4	✗	✗	✗	✗
229	Sylvania	QT 2x32277 IS-SC	IS	2	N/A	✓	N/A	✓
230	Sylvania	QT 3x32/277 IS	IS	3	N/A	✗	N/A	✗
231	TCP	E2P32ISUNVHE	IS	2	✓	✗	✓	✓
232	TCP	E3P32ISUNVE	IS	3	✓	✓	✓	✓
233	TCP	E3P32ISUNVHE	IS	3	✓	✓	✓	✓
234	TCP	E3P32ISUNVLE	IS	3	✓	✗	✓	✓
235	TCP	E4P32ISUNVE	IS	4	✓	✓	✓	✓

Ballast Description					Reduced Lamp Load*		Rated Lamp Load	
No.	Brand	Model	Start Method	No. of Lamps	120V	277V	120V	277V
236	TCP	E4P32ISUNVLE	IS	4	✓	✗	✓	✗
237	TCP	TCP3P32ISUNVH	IS	3	✓	✓	✓	✓
238	Topaz	B232IUNVHEH/A-TPZ	IS	2	✓	✓	✓	✓
239	Topaz	B432IUNVHEH/A-TPZ	IS	4	✓	✓	✓	✓
240	Universal Lighting Technologies	B132IUNVEL-A	IS	1	N/A	N/A	✓	✓
241	Universal Lighting Technologies	B132IUNVHP-N	IS	1	N/A	N/A	✓	✗
242	Universal Lighting Technologies	B232I120RES-A	IS	2	✗	N/A	✗	N/A
243	Universal Lighting Technologies	B232I277RH-A	IS	4	N/A	✓	N/A	✓
244	Universal Lighting Technologies	B232IUNV-C	IS	2	✓	✓	✓	✓
245	Universal Lighting Technologies	B232IUNVEL-A	IS	2	✓	✓	✓	✓
246	Universal Lighting Technologies	B232IUNVHP-B	IS	2	✓	✓	✓	✓
247	Universal Lighting Technologies	B232IUNVHP-N	IS	2	✓	✓	✓	✓
248	Universal Lighting Technologies	B232PU104S50A	PRS	2	✗	✗	✗	✗
249	Universal Lighting Technologies	B232PUNVHE-B	PS	2	✓	✓	✓	✓
250	Universal Lighting Technologies	B232PUNVHP-A	PS	2	✗	✗	✗	✗
251	Universal Lighting Technologies	B233IUNVHE-A	IS	2	✓	✓	✓	✓
252	Universal Lighting Technologies	B332I277RH-A	IS	3	N/A	✓	N/A	✓
253	Universal Lighting Technologies	B332IHRVHB-E	IS	3	✗	✗	✗	✗
254	Universal Lighting Technologies	B332IUNVHP-A	IS	3	✓	✓	✓	✓
255	Universal Lighting Technologies	B332PUNVHEH-A	PS	3	✓	✓	✓	✓
256	Universal Lighting Technologies	B432IUNVHE L-A	IS	4	✓	✓	✓	✓
257	Universal Lighting Technologies	B432IUNVHE-A	IS	4	✓	✓	✓	✓
258	Universal Lighting Technologies	B432IUNVHEH-E	IS	4	✓	✓	✓	✓
259	Universal Lighting Technologies	B432IUNVHP-A	IS	4	✓	✓	✓	✓
260	Universal Lighting Technologies	B432PUNVHE-A	PS	4	✓	✓	✓	✓
261	Watran	DB-232N-MV-TP-HE	IS	2	✓	✓	✓	✓
262	Watran	DB-232N-MV-TP-HE SC	IS	2	✓	✓	✓	✓
263	Watran	DB-332N-MV-TP-HE	IS	3	✓	✓	✓	✓
264	Watran	DB-432L-MV-TP-HE	IS	4	✓	✓	✓	✓
265	Watran	DB-432N-MV-TP-HE	IS	4	✓	✓	✓	✓

Ballast Description					Reduced Lamp Load*		Rated Lamp Load	
No.	Brand	Model	Start Method	No. of Lamps	120V	277V	120V	277V
266	Watran	DBG32N-MV-TP-PS-HL	PS	3	✗	✗	✗	✗
267	Work Horse	WHS3G3-UNV-T8-IS	IS	3	✓	✓	✓	✓
268	Work Horse	WHS4G4-UNV-T8-IS	IS	4	✓	✓	✓	✓

Ballast Description (347-480V)					Reduced Lamp Load*		Rated Lamp Load	
No.	Brand	Model	Start Method	No. of Lamps	347V	480V	347V	480V
270	General Electric	GE432MAX347-N	IS	4	✓	N/A	✓	N/A
271	Osram	QHE 2x32T8/347 PSN-SC	PRS	2	✗	✗	✗	✗
272	Osram	QHE 2X32T8/347 ISN-SC	IS	2	✓	N/A	✓	N/A
273	Osram	QHE 4X32T8/347 ISN-SC	IS	4	✓	N/A	✓	N/A
274	Osram Sylvania	QT 2x32/347 ISH-SC	IS	2	N/A	N/A	✓	N/A
275	Philips-Advance	GOPA-2P32-N	IS	2	✗	N/A	✗	N/A
276	Sylvania	QT 2X32/347LP	IS	2	✗	N/A	✗	N/A
277	Sylvania	QT 4x32 T8/347 ISN-SC	IS	4	✓	N/A	✓	N/A
278	Sylvania	QT 4X32/347LP	IS	4	✓	N/A	✓	N/A
279	Universal Lighting Technologies	B432I347HE-A	IS	4	✗	N/A	✗	N/A